


**Anritsu** envision : ensure

# Remote Spectrum Monitors

For Remote RF Signal Monitoring

## MS27103A

9 kHz to 6 GHz



## Introduction

The MS27103A provides 12 RF Input ports as a standard configuration (24 RF Input ports are available with Option 424). This model is typically used with three or six sector BTS architectures, with multiple carriers per sector. A high speed switch is placed in the monitor to provide measurement capability for each RF input. A greater than 30 dB isolation is provided between each RF Input port to assure the integrity of the measurement.

## Remote Spectrum Monitor Highlights

- Sweep rates up to 24 GHz/s
- Integrated web server to view, control, and conduct measurements via a web browser (Chrome or Firefox)
- Remote firmware updates
- Watchdog timer to insure long-term stability for remotely deployed monitors
- Low spurious signals for accurate signal discovery
- 20 MHz IF bandwidth
- Low power consumption < 11 watts
- Integrated GPS receiver for monitoring location and time synchronization applications
- Gigabit Ethernet available for high speed communications
- Measurements: occupied bandwidth and channel power
- Interference analysis: spectrogram and signal strength
- Dynamic range: > 106 dB normalized to 1 Hz BW
- Phase noise: -98 dBc/Hz @ 10 kHz offset at 1 GHz
- Frequency accuracy: < ±1.5 ppm, < ±50 ppb with GPS High Accuracy Mode
- IQ block mode and streaming with time stamping for time difference of arrival (TDOA) applications
- Remote control via SCPI commands
- Vision™ software optional for automated spectrum measurements, setting alarms, and geo-locating signal sources
- SpectraVision software optional for TETRA and Satellite measurements and Channel scanning



MS27103A Remote Spectrum Monitor  
(front and rear sides shown, Option 110 replaces screw terminal with 3-pin AC line receptacle)

**Table of Contents**

Definitions. . . . . 3  
 Remote Spectrum Monitor. . . . . 4  
 General Specifications . . . . . 6  
 Ordering Information . . . . . 7

**Definitions**

All specifications and characteristics apply under the following conditions, unless otherwise stated:

Warm-Up Time	After 10 minutes of warm-up time, where the instrument is left in the On state.
Temperature Range	Over the 23 °C ±5 °C temperature range.
Typical Performance	Typical specifications in parenthesis () describe performance that will be met by a minimum of 80% of all products. They do not include guard bands and are not warranted. Typical specifications that are not in parenthesis are not tested and not warranted. They are generally representative of the nominal characteristic performance.
Uncertainty	A coverage factor of $k = 2$ is applied to the measurement uncertainties to facilitate comparison with other industry monitors. All specifications subject to change without notice. For the most current data sheet, please visit the Anritsu web site: <a href="http://www.anritsu.com">www.anritsu.com</a>

## Remote Spectrum Monitor

<b>Frequency</b>		Frequency Range	9 kHz to 6 GHz (tunable to 0 Hz)	
		Tuning Resolution	1 Hz	
		Frequency Reference	Accuracy: $\pm 1.5$ ppm ( $25\text{ }^{\circ}\text{C} \pm 25\text{ }^{\circ}\text{C}$ ) $\pm 1.0$ ppm/year aging < $\pm 50$ ppb with GPS on	
		Frequency Span	10 Hz to 6 GHz	
<b>Sweep Speed</b>		Typical (full span FTT mode)		
		10 kHz RBW	5 GHz/s	
		30 kHz RBW	12 GHz/s	
		3 MHz RBW	24 GHz/s	
<b>Bandwidth</b>		Resolution Bandwidth (RBW)	10 Hz to 3 MHz in 1–3 sequence (–3 dB bandwidth)	
		Video Bandwidth (VBW)	10 Hz to 3 MHz in 1–3 sequence (–3 dB bandwidth) (auto or manually selectable)	
<b>Spectral Purity</b>		SSB Phase Noise @ 1 GHz	(-98 dBc/Hz) @ 10 kHz offset (-98 dBc/Hz) @ 100 kHz offset	
<b>Amplitude Ranges</b>		Dynamic Range	> 106 dB (2.4 GHz), 2/3 (TOI-DANL) in 1 Hz RBW	
		Measurement Range	DANL to Maximum Continuous Input	
		Reference Level Range	–150 dBm to +30 dBm	
		Attenuator Range	0 dB to 50 dB in 5 dB steps	
		Amplitude Units	Log Scale Modes: dBm, dB $\mu$ V	
		Maximum Continuous Input	100 MHz to 6 GHz, $\geq 10$ dB attenuation 300 kHz to 6 GHz, < 10 dB attenuation 9 kHz to 6 GHz, preamp on	
			+22 dBm <sup>a</sup> , $\pm 50$ VDC +10 dBm <sup>a</sup> , $\pm 50$ VDC –10 dBm, $\pm 50$ VDC	
			a. For lower frequencies, derate maximum continuous input by 4 dB per decade	
<b>Amplitude Accuracy</b>		Attenuation $\leq 40$ dB, preamp off for frequencies less than 100 kHz		
		Port 1 (dB)	Ports 2 to 12 (dB, typical)	Option 424 (24 Ports) Ports 13 to 24 (dB, typical)
		9 kHz to 5 GHz	$\pm 2.5$	$\pm 3.0$
		> 5 GHz to 6 GHz	$\pm 3.0$	$\pm 3.5$
<b>Displayed Average Noise Level (DANL)</b>		RBW normalized to 1 Hz, 0 dB attenuation (Port 1 is specified. All other ports are typical and within 1 dB of the specified values)		
		Preamp Off, Reference Level –20 dBm		Preamp On, Reference Level –50 dBm
		Port 1 (dBm)	Typical (dBm)	Port 1 (dBm)
		10 MHz to 3.3 GHz	–140	–145
		> 3.3 GHz to 4.1 GHz	–133	–152
		> 4.1 GHz to 5 GHz	–130	–148
		> 5 GHz to 6 GHz	–115	–133
				–160
				–155
				–152
				–141
<b>Spurs</b>		Typical		
		Residual Spurious	RF input terminated, 0 dB input attenuation, preamp off (< –80 dBm), 10 MHz to 4.5 GHz (< –70 dBm), >4.5 GHz to 6.0 GHz	
			RF input terminated, 0 dB input attenuation, preamp on (< –95 dBm), 10 MHz to 5.0 GHz (< –88 dBm), 16 MHz to 18 MHz (< –85 dBm), >5.0 GHz to 6.0 GHz	
		Input-Related Spurious	< –60 dBc, 0 dB attenuation, –30 dBm input, carrier offset > 5 MHz	
<b>Second Harmonic Distortion</b>		Typical; 0 dB attenuation, –30 dBm input		
		50 MHz	(–50 dBc)	
		> 50 MHz to 200 MHz	< –60 dBc	
		> 200 MHz to 3000 MHz	< –60 dBc	
<b>Third-Order Intercept (TOI)</b>		Typical; preamp off, –20 dBm tones 100 kHz apart, 0 dB attenuation, reference level –20 dBm		
		800 MHz	(+7 dBm)	
		2400 MHz	(+17 dBm)	
		200 to 2200 MHz	+10 dBm	
		>2.2 GHz to 5.0 GHz	+8 dBm	
		>5.0 GHz to 6.0 GHz	+14 dBm	

**Remote Spectrum Monitor** (continued)

<b>VSWR</b>	< 2.5:1 typical	
<b>Signal Processing</b>		
Data Types	I/Q time series: 8, 10, 16 or 24 bit resolution Spectrum trace: 100 to 4000 points	
Data Transfer Modes	I/Q time series or spectrum trace in streaming or block mode	
I/Q Data Streaming Rate	Gapless on 100Base-T network, Up to 2.6 MHz signal bandwidth	
I/Q Data Time Stamp Resolution	8.7 ns	

<b>Antenna Port Isolation</b>	Typical
≤ 3 GHz	> 40 dB
> 3 GHz	> 30 dB

Signal Bandwidth	I/Q Recording Time Typical		Output Data Rate			
	MSPS	I/Q Bit Resolution	24 bits	16 bits	10 bits	8 bits
20 MHz	76.25 / 3	1.3 s	2.5 s	3.8 s	5 s	
13.3 MHz	76.25 / 4	1.7 s	3.4 s	5 s	6.7 s	
6.67 MHz	76.25 / 8	3.4 s	6.7 s	10.1 s	13.4 s	
2.67 MHz	76.25 / 20	8.4 s	16.8 s	25.2 s	33.6 s	
1.33 MHz	76.25 / 40	16.8 s	33.6 s	50.4 s	1.12 min	
667 kHz	76.25 / 80	33.6 s	1.12 min	1.68 min	2.24 min	
267 kHz	76.25 / 200	1.4 min	2.8 min	4.2 min	5.6 min	
133 kHz	76.25 / 400	2.8 min	5.6 min	8.39 min	11.19 min	
66.7 kHz	76.25 / 800	5.6 min	11.19 min	16.79 min	22.38 min	
26.7 kHz	76.25 / 2000	13.99 min	27.98 min	41.97 min	55.96 min	
13.3 kHz	76.25 / 4000	27.98 min	55.96 min	1.4 h	1.87 h	
6.67 kHz	76.25 / 8000	55.96 min	1.87 h	2.8 h	3.73 h	
2.67 kHz	76.25 / 20000	2.33 h	4.66 h	6.99 h	9.33 h	
1.33 kHz	76.25 / 40000	4.66 h	9.33 h	13.99 h	18.65 h	

## General Specifications

### Setup Parameters

System Status	Temperature, Serial Number, Firmware Version, Options Installed, Self Test, Application Self Test, GPS
System Options	Name, Date and Time, Reset (Factory Defaults, Master Reset, Update Firmware)
Directory Management	Sort Method (Name/Type/Date), Ascend/Descend, Internal/USB, Copy
Internal Trace/Setup Memory	4 GB internal memory available for storing files
Mode Switching	Automatically stores/recalls most recently used setup parameters in the mode

### Connectors

RF In	12 SMA(f) ports, 50 $\Omega$ 24 SMA(f) ports, 50 $\Omega$ (optional)
External Power	11 W, $\pm 20$ VDC to $\pm 70$ VDC (110/220 VAC optional)
Ethernet	One RJ45 connector for Gbit LAN, 2nd port optional for daisy chain
USB	Two USB Type A connectors
External Reference In	10 MHz, +10 dBm max, +5 VDC max, BNC(f)
GPS	SMA(f)

### Regulatory Compliance

European Union	EMC 2014/30/EU, EN 61326:2013, CISPR 11/EN 55011, IEC/EN 61000-4-2/3/4/5/6/8/11 Low Voltage Directive 2014/35/EU Safety EN 61010-1:2010 RoHS Directive 2011/65/EU
Australia and New Zealand	RCM AS/NZS 4417:2012
South Korea	KCC-REM-A21-0004

### Environmental

	MIL-PRF-28800F Class 3
Operating Temperature Range	0 °C to 50 °C
Storage Temperature Range	-40 °C to 71 °C
Maximum Relative Humidity	95 % RH at 30 °C, non-condensing
Vibration, Sinusoidal	5 Hz to 55 Hz
Vibration, Random	10 Hz to 500 Hz
Half Sine Shock	30 g <sub>n</sub>
Altitude	4600 meters, operating and non-operating

### ESD

RF Input Pin	Withstands up to $\pm 4$ kV
--------------	-----------------------------

### Size and Weight

Size	480 mm x 90 mm x 300 mm (18.9 in x 3.5 in x 11.8 in)
Weight	12-port: 3.9 kg (8.9 lb) 24-port: 4.5 kg (9.9 lb)

### Warranty

Instrument	Standard three-year warranty
------------	------------------------------



Ordering Information

Standard Hardware

Model Number	Description
MS27103A	Spectrum Monitor with 12 SMA(f) Input Ports (requires frequency option below)

Hardware Options

Option Number	Description
MS27103A-0706	9 kHz to 6 GHz Frequency Range
MS27103A-0424	Expands Input Ports to 24 SMA(f)
MS27103A-0110	110/220 VAC Power Supply
MS27103A-0412	Two Ethernet Ports

Software Options

Option Number	Description
MS27103A-0400	Vision Monitor Enabled
MS27103A-0401	Vision Locate Enabled (requires Option 400 above)
MS27103A-0407	Vision High-Speed Port Scanner Enabled
MS27103A-0464	SpectraVision TETRA Enabled
MS27103A-0467	SpectraVision Scanner Enabled
MS27103A-0471	SpectraVision Satellite Enabled

Standard Accessories (included with instrument)

Part Number	Description
2000-1371-R	Ethernet Cable, 2.13 m (7 ft)
2000-1528-R	GPS Antenna, SMA(m) with 5 m (15 ft) cable, 3 dBi gain, requires 5 VDC

Optional Accessories



Part Number	Description
760-287-R	Large Transit Case with Wheels and Handle

# Training at Anritsu

Anritsu has designed courses to help you stay up to date with technologies important to your job. For available training courses, visit: [www.anritsu.com/training](http://www.anritsu.com/training)



## • United States

### Anritsu Company

1155 East Collins Blvd, Suite 100  
Richardson, TX 75081, U.S.A.  
Toll Free: 1-800-267-4878  
Phone: +1-972-644-1777  
Fax: +1-972-671-1877

## • Canada

### Anritsu Electronics Ltd.

700 Silver Seven Road, Suite 120  
Kanata, Ontario K2V 1C3, Canada  
Phone: +1-613-591-2003  
Fax: +1-613-591-1006

## • Brazil

### Anritsu Eletrônica Ltda.

Praça Amadeu Amaral, 27 - 1 Andar  
01327-010 Bela Vista, São Paulo, SP, Brazil  
Phone: +55-11-3283-2511  
Fax: +55-11-3288-6940

## • Mexico

### Anritsu Company, S.A. de C.V.

Av. Ejército Nacional No. 579 Piso 9, Col. Granada  
11520 México, D.F., México  
Phone: +52-55-1101-2370  
Fax: +52-55-5254-3147

## • United Kingdom

### Anritsu EMEA Ltd.

200 Capability Green  
Luton, Bedfordshire LU1 3LU  
United Kingdom  
Phone: +44-1582-433280  
Fax: +44-1582-731303

## • France

### Anritsu S.A.

12 Avenue du Québec  
Bâtiment Iris 1-Silic 612  
91140 Villebon-sur-Yvette, France  
Phone: +33-1-60-92-15-50  
Fax: +33-1-64-46-10-65

## • Germany

### Anritsu GmbH

Nemetschek Haus, Konrad-Zuse-Platz 1  
81829 München, Germany  
Phone: +49-89-442308-0  
Fax: +49-89-442308-55

## • Italy

### Anritsu S.r.l.

Via Elio Vittorini 129  
00144 Roma, Italy  
Phone: +39-06-509-9711  
Fax: +39-06-502-2425

## • Sweden

### Anritsu AB

Kistagången 20B  
164 40 KISTA, Sweden  
Phone: +46-8-534-707-00  
Fax: +46-8-534-707-30

## • Finland

### Anritsu AB

Teknobulevardi 3-5  
FI-01530 Vantaa, Finland  
Phone: +358-20-741-8100  
Fax: +358-20-741-8111

## • Denmark

### Anritsu A/S

Kay Fiskers Plads 9  
2300 Copenhagen S, Denmark  
Phone: +45-7211-2200  
Fax: +45-7211-2210

## • Russia

### Anritsu EMEA Ltd.

**Representation Office in Russia**  
Tverskaya str. 16/2, bld. 1, 7th floor  
Moscow, 125009, Russia  
Phone: +7-495-363-1694  
Fax: +7-495-935-8962

## • Spain

### Anritsu EMEA Ltd.

**Representation Office in Spain**  
Edificio Cuzco IV, Po. de la Castellana, 141, Pta. 8  
28046, Madrid, Spain  
Phone: +34-915-726-761  
Fax: +34-915-726-621

## • United Arab Emirates

### Anritsu EMEA Ltd.

**Dubai Liaison Office**  
902, Aurora Tower,  
P O Box: 500311- Dubai Internet City  
Dubai, United Arab Emirates  
Phone: +971-4-3758479  
Fax: +971-4-4249036

## • India

### Anritsu India Private Limited

2nd & 3rd Floor, #837/1, Binnamangla 1st Stage  
Indiranagar, 100ft Road, Bangalore - 560038, India  
Phone: +91-80-4058-1300  
Fax: +91-80-4058-1301

## • Singapore

### Anritsu Pte. Ltd.

11 Chang Charn Road, #04-01, Shiro House  
Singapore 159640  
Phone: +65-6282-2400  
Fax: +65-6282-2533

## • P.R. China (Shanghai)

### Anritsu (China) Co., Ltd.

27th Floor, Tower A  
New Caohejing International Business Center  
No. 391 Gui Ping Road Shanghai, Xu Hui Di District  
Shanghai 200233, P.R. China  
Phone: +86-21-6237-0898  
Fax: +86-21-6237-0899

## • P.R. China (Hong Kong)

### Anritsu Company Ltd.

Unit 1006-7, 10/F., Greenfield Tower  
Concordia Plaza  
No. 1 Science Museum Road, Tsim Sha Tsui East  
Kowloon, Hong Kong, P. R. China  
Phone: +852-2301-4980  
Fax: +852-2301-3545

## • Japan

### Anritsu Corporation

8-5, Tamura-cho, Atsugi-shi  
Kanagawa, 243-0016 Japan  
Phone: +81-46-296-1221  
Fax: +81-46-296-1238

## • Korea

### Anritsu Corporation, Ltd.

5FL, 235 Pangyoyeok-ro, Bundang-gu, Seongnam-si  
Gyeonggi-do, 13494 Korea  
Phone: +82-31-696-7750  
Fax: +82-31-696-7751

## • Australia

### Anritsu Pty. Ltd.

Unit 20, 21-35 Ricketts Road,  
Mount Waverley, Victoria 3149, Australia  
Phone: +61-3-9558-8177  
Fax: +61-3-9558-8255

## • Taiwan

### Anritsu Company Inc.

7F, No. 316, Sec. 1, Neihu Rd, Taipei 114, Taiwan  
Phone: +886-2-8751-1816  
Fax: +886-2-8751-1817

List Revision Date: 20160317