



# Remote Spectrum Monitors

For Remote RF Signal Monitoring

## MS27102A

9 kHz to 6 GHz



## Introduction

The Anritsu platform of spectrum monitors provides high performance real-time monitoring of the radio spectrum. Designed to be stable over time under continuous operation, the MS27102A monitor provides superior sweep speeds, high dynamic range, and low spurious levels for fast and accurate measurements. Applications include monitoring for interference, white space analysis, unlicensed transmission discovery, and signal coverage.

The MS27102A features an IP67 rated outdoor enclosure designed for remote operations in the harshest of environments. The MS27102A is available as a single port RF-IN instrument with an option for two ports that enable the use of multiple antennas.

## Remote Spectrum Monitor Highlights

- Sweep rates up to 24 GHz/s
- Integrated web server to view, control, and conduct measurements via a web browser (Chrome or Firefox)
- Remote firmware updates
- Watchdog timer to insure long-term stability for remotely deployed monitors
- Low spurious signals for accurate signal discovery
- 20 MHz IF bandwidth
- Low power consumption < 11 watts
- Integrated GPS receiver for monitoring location and time synchronization applications
- Gigabit Ethernet available for high speed communications
- Measurements: occupied bandwidth, channel power
- Interference analysis: spectrogram and signal strength
- Dynamic range: > 106 dB normalized to 1 Hz BW
- Phase noise: -98 dBc/Hz @ 10 kHz offset at 1 GHz
- Frequency accuracy: < ±1.5 ppm, < ±50 ppb with GPS High Accuracy Mode
- IQ block mode and streaming with time stamping for time difference of arrival (TDOA) applications
- Remote control via SCPI commands
- Vision™ software optional for automated spectrum measurements, setting alarms, and geo-locating signal sources
- SpectraVision software optional for TETRA and Satellite measurements and Channel scanning



MS27102A Remote Spectrum Monitor

**Table of Contents**

Definitions.....	3
Remote Spectrum Monitor.....	4
Multiple RF Input Ports (Option 402, 404, and 406).....	5
General Specifications .....	6
Ordering Information.....	7

**Definitions**

Warm-Up Time	All specifications and characteristics apply under the following conditions, unless otherwise stated: After 10 minutes of warm-up time, where the instrument is left in the on state.
Temperature Range	Over the 23 °C ±5 °C temperature range.
Typical Performance	Typical specifications in parenthesis () describe performance that will be met by a minimum of 80% of all products. They do not include guard bands and are not warranted. Typical specifications that are not in parenthesis are not tested and not warranted. They are generally representative of the nominal characteristic performance.
Uncertainty	A coverage factor of k = 2 is applied to the measurement uncertainties to facilitate comparison with other industry monitors. All specifications subject to change without notice. For the most current data sheet, please visit the Anritsu web site: <a href="http://www.anritsu.com">www.anritsu.com</a>

## Remote Spectrum Monitor

<b>Frequency</b>			
Frequency Range	9 kHz to 6 GHz (tunable to 0 Hz)		
Tuning Resolution	1 Hz		
Frequency Reference	Accuracy: $\pm 1.5 \text{ ppm}$ ( $25^\circ\text{C} \pm 25^\circ\text{C}$ ) $\pm 1.0 \text{ ppm/year aging}$ $< \pm 50 \text{ ppb}$ with GPS on		
Frequency Span	10 Hz to 6 GHz		
<b>Sweep Speed</b>			
Typical (full span FFT mode)			
10 kHz RBW	5 GHz/s		
30 kHz RBW	12 GHz/s		
3 MHz RBW	24 GHz/s		
<b>Bandwidth</b>			
Resolution Bandwidth (RBW)	10 Hz to 3 MHz in 1-3 sequence (-3 dB bandwidth)		
Video Bandwidth (VBW)	10 Hz to 3 MHz in 1-3 sequence (-3 dB bandwidth) (auto or manually selectable)		
<b>Spectral Purity</b>			
SSB Phase Noise @ 1 GHz	(-98 dBc/Hz) @ 10 kHz offset (-98 dBc/Hz) @ 100 kHz offset		
<b>Amplitude Ranges</b>			
Dynamic Range	(> 106 dB at 2.4 GHz), 2/3 (TOI-DANL) in 1 Hz RBW		
Measurement Range	DANL to Maximum Continuous Input		
Reference Level Range	-150 dBm to +30 dBm		
Attenuator Range	0 dB to 50 dB in 5 dB steps		
Amplitude Units	Log Scale Modes: dBm, dB $\mu$ V		
Maximum Continuous Input	(without Option 402, 404, or 406)	with Option 402, 404, or 406	
100 MHz to 6 GHz, $\geq 10$ dB attenuation	+30 dBm <sup>a</sup> , $\pm 50$ VDC	+20 dBm <sup>b</sup> , $\pm 50$ VDC	
300 kHz to 6 GHz, < 10 dB attenuation	+10 dBm <sup>a</sup> , $\pm 50$ VDC	+10 dBm <sup>b</sup> , $\pm 50$ VDC	
9 kHz to 6 GHz, preamp on	-10 dBm, $\pm 50$ VDC	-10 dBm, $\pm 50$ VDC	
a. For lower frequencies, derate maximum continuous input by 6 dB per decade			
b. For lower frequencies, derate maximum continuous input by 4 dB per decade			
<b>Amplitude Accuracy</b>			
Attenuation $\leq 40$ dB, preamp off for frequencies less than 100 kHz			
9 kHz to 6.0 GHz	$\pm 2.5$ dB		
<b>Displayed Average Noise Level (DANL)</b>			
RBW normalized to 1 Hz, 0 dB attenuation			
Preamp Off, Reference Level -20 dBm			
Max (dBm)	Typical (dBm)	Preamp On, Reference Level -50 dBm	
10 MHz to 3.3 GHz	-145	-150	Max (dBm)
> 3.3 GHz to 4.1 GHz	-140	-145	Typical (dBm)
> 4.1 GHz to 5 GHz	-138	-143	-162
> 5 GHz to 6 GHz	-128	-136	-159
			-156
			-160
			-146
			-154
<b>Spurs</b>			
Typical			
Residual Spurious	(< -80 dBm) RF input terminated, 0 dB input attenuation, preamp off, > 10 MHz (< -95 dBm) RF input terminated, 0 dB input attenuation, preamp on, > 10 MHz (< -88 dBm) RF input terminated, 0 dB input attenuation, preamp on, 16 MHz to 18 MHz		
Input-Related Spurious	< -60 dBc, 0 dB attenuation, -30 dBm input, carrier offset > 5 MHz		
Exceptions	< -60 dBc, input = 4140 MHz		
<b>Second Harmonic Distortion</b>			
Typical; 0 dB attenuation, -30 dBm input			
50 MHz	(-50 dBc)		
> 50 MHz to 200 MHz	< -60 dBc		
> 200 MHz to 3000 MHz	< -60 dBc		
<b>Third-Order Intercept (TOI)</b>			
Typical; preamp off, -20 dBm tones 100 kHz apart, 0 dB attenuation, reference level -20 dBm			
800 MHz	(+7 dBm)		
2400 MHz	(+17 dBm)		
200 to 2200 MHz	+10 dBm		
> 2.2 GHz to 5.0 GHz	+8 dBm		
> 5.0 GHz to 6.0 GHz	+14 dBm		

## Specifications

MS27102A

### Remote Spectrum Monitor (continued)

<b>VSWR</b>	< 2.5:1 typical
<b>Signal Processing</b>	
Data Types	I/Q time series: 8, 10, 16 or 24 bit resolution Spectrum trace: 100 to 4000 points
Data Transfer Modes	I/Q time series or spectrum trace in streaming or block mode
I/Q Data Streaming Rate	Gapless on 100Base-T network, Up to 2.6 MHz signal bandwidth
I/Q Data Time Stamp Resolution	8.7 ns
<b>I/Q Recording Time</b> Typical	
Signal Bandwidth	Output Data Rate I/Q Bit Resolution
	MSPS 24 bits 16 bits 10 bits 8 bits
20 MHz	76.25 / 3 1.3 s 2.5 s 3.8 s 5 s
13.3 MHz	76.25 / 4 1.7 s 3.4 s 5 s 6.7 s
6.67 MHz	76.25 / 8 3.4 s 6.7 s 10.1 s 13.4 s
2.67 MHz	76.25 / 20 8.4 s 16.8 s 25.2 s 33.6 s
1.33 MHz	76.25 / 40 16.8 s 33.6 s 50.4 s 1.12 min
667 kHz	76.25 / 80 33.6 s 1.12 min 1.68 min 2.24 min
267 kHz	76.25 / 200 1.4 min 2.8 min 4.2 min 5.6 min
133 kHz	76.25 / 400 2.8 min 5.6 min 8.39 min 11.19 min
66.7 kHz	76.25 / 800 5.6 min 11.19 min 16.79 min 22.38 min
26.7 kHz	76.25 / 2000 13.99 min 27.98 min 41.97 min 55.96 min
13.3 kHz	76.25 / 4000 27.98 min 55.96 min 1.4 h 1.87 h
6.67 kHz	76.25 / 8000 55.96 min 1.87 h 2.8 h 3.73 h
2.67 kHz	76.25 / 20000 2.33 h 4.66 h 6.99 h 9.33 h
1.33 kHz	76.25 / 40000 4.66 h 9.33 h 13.99 h 18.65 h

### Multiple RF Input Ports (Option 402, 404, and 406) (provides two, four, or six RF input ports)

<b>Amplitude Accuracy</b>	Attenuation $\leq$ 40 dB, preamp off for frequencies less than 100 kHz
9 kHz to 5 GHz	$\pm 2.5$ dB
> 5 GHz to 6.0 GHz	$\pm 3$ dB
<b>Displayed Average Noise Level (DANL)</b> RBW normalized to 1 Hz, 0 dB attenuation	
	Preamp Off, Reference Level -20 dBm
	Max (dBm) Typical (dBm)
10 MHz to 3.3 GHz	-140 -147
> 3.3 GHz to 4.1 GHz	-135 -142
> 4.1 GHz to 5 GHz	-133 -139
> 5 GHz to 6 GHz	-117 -129
<b>Antenna Port Isolation</b>	
	Typical
$\leq$ 3 GHz	> 40 dB
> 3 GHz	> 30 dB



MS27102A Remote Spectrum Monitor, rear panel connectors with Option 406

## General Specifications

<b>Setup Parameters</b>	
System Status	Temperature, Serial Number, Firmware Version, Options Installed, Self Test, Application Self Test, GPS
System Options	Name, Date and Time, Reset (Factory Defaults, Master Reset, Update Firmware)
Directory Management	Sort Method (Name/Type/Date), Ascend/Descend, Internal/USB, Copy
Internal Trace/Setup Memory	4 GB internal memory available for storing files
Mode Switching	Automatically stores/recalls most recently used setup parameters in the mode
<b>Connectors</b>	
RF In	One type N, female port, 50 Ω
	Two, four, or six type N, female ports, 50 Ω (Option 402, 404, or 406)
External Power	11 W, 11 V to 24 V, 3-pin IP67 power connector
Ethernet	1 RJ45 connector for Gbit LAN (ruggedized and weatherproof)
GPS	SMA(f)
<b>Regulatory Compliance</b>	
European Union	EMC 2014/30/EU, EN 61326:2013, CISPR 11/EN 55011, IEC/EN 61000-4-2/3/4/5/6/8/11 Low Voltage Directive 2014/35/EU Safety EN 61010-1:2010
Australia and New Zealand	RoHS Directive 2011/65/EU
South Korea	RCM AS/NZS 4417:2012
	KCC-REM-A21-0004
<b>Environmental</b>	
Operating Temperature Range	MIL-PRF-28800F Class 2
Storage Temperature Range	-40 °C to 55 °C
Maximum Relative Humidity	-51 °C to 71 °C
Vibration, Sinusoidal	95 % RH at 30 °C, non-condensing
Vibration, Random	5 Hz to 55 Hz
Half Sine Shock	10 Hz to 500 Hz
Altitude	30 g <sub>n</sub>
Explosive Atmosphere	4600 meters, operating and non-operating
	MIL-PRF-28800F, Section 4.5.6.3
	MIL-STD-810G, Method 511.5, Procedure 1
<b>ESD</b>	
RF Input Pin	Withstands up to ±4 kV
<b>Size and Weight</b>	
Size	310 mm x 102 mm x 310 mm (12.2 in x 4.0 in x 12.2 in)
Weight	6.87 kg (15.2 lb)
<b>Warranty</b>	
Instrument	Standard three-year warranty

**Ordering Information****Standard Hardware**

<b>Model Number</b>	<b>Description</b>
MS27102A	Spectrum Monitor with 1 RF IN Port (requires one frequency option)

**Hardware Options**

<b>Option Number</b>	<b>Description</b>
MS27102A-0706	9 kHz to 6 GHz Frequency Range
MS27102A-0402	2 RF IN Ports
MS27102A-0404	4 RF IN Ports
MS27102A-0406	6 RF IN Ports

**Software Options**

<b>Option Number</b>	<b>Description</b>
MS27102A-0400	Vision Monitor Enabled
MS27102A-0401	Vision Locate Enabled (requires Option 400 above)
MS27102A-0407	Vision High-Speed Port Scanner Enabled
MS27102A-0464	SpectraVision TETRA Enabled
MS27102A-0467	SpectraVision Scanner Enabled
MS27102A-0471	SpectraVision Satellite Enabled

**Standard Accessories** (included with instrument)

<b>Part Number</b>	<b>Description</b>
40-187-R	AC-DC Adapter
2100-32-R	Power Adapter
2000-1371-R	Ethernet Cable, 2.13 m (7 ft)
2000-1528-R	GPS Antenna, SMA(m) with 5 m (15 ft) cable, 3 dBi gain, requires 5 VDC

**Optional Accessories**

<b>Part Number</b>	<b>Description</b>
760-285-R	Large Transit Case with Wheels and Handle



# Training at Anritsu

Anritsu has designed courses to help you stay up to date with technologies important to your job. For available training courses, visit: [www.anritsu.com/training](http://www.anritsu.com/training)



## • United States

### Anritsu Company

1155 East Collins Blvd, Suite 100  
Richardson, TX 75081, U.S.A.  
Toll Free: 1-800-267-4878  
Phone: +1-972-644-1777  
Fax: +1-972-671-1877

## • Canada

### Anritsu Electronics Ltd.

700 Silver Seven Road, Suite 120  
Kanata, Ontario K2V 1C3, Canada  
Phone: +1-613-591-2003  
Fax: +1-613-591-1006

## • Brazil

### Anritsu Electrônica Ltda.

Praça Amadeu Amaral, 27 - 1 Andar  
01327-010 Bela Vista, São Paulo, SP, Brazil  
Phone: +55-11-3283-2511  
Fax: +55-11-3288-6940

## • Mexico

### Anritsu Company, S.A. de C.V.

Av. Ejército Nacional No. 579 Piso 9, Col. Granada  
11520 México, D.F., México  
Phone: +52-55-1101-2370  
Fax: +52-55-5254-3147

## • United Kingdom

### Anritsu EMEA Ltd.

200 Capability Green  
Luton, Bedfordshire LU1 3LU  
United Kingdom  
Phone: +44-1582-433280  
Fax: +44-1582-731303

## • France

### Anritsu S.A.

12 Avenue du Québec  
Bâtiment Iris 1-Silic 612  
91140 Villebon-sur-Yvette, France  
Phone: +33-1-60-92-15-50  
Fax: +33-1-64-46-10-65

## • Germany

### Anritsu GmbH

Nemetschek Haus, Konrad-Zuse-Platz 1  
81829 München, Germany  
Phone: +49-89-442308-0  
Fax: +49-89-442308-55

## • Italy

### Anritsu S.r.l.

Via Elio Vittorini 129  
00144 Roma, Italy  
Phone: +39-06-509-9711  
Fax: +39-06-502-2425

## • Sweden

### Anritsu AB

Kistagången 20B  
164 40 KISTA, Sweden  
Phone: +46-8-534-707-00  
Fax: +46-8-534-707-30

## • Finland

### Anritsu AB

Teknobulevardi 3-5  
FI-01530 Vantaa, Finland  
Phone: +358-20-741-8100  
Fax: +358-20-741-8111

## • Denmark

### Anritsu A/S

Kay Fiskers Plads 9  
2300 Copenhagen S, Denmark  
Phone: +45-7211-2200  
Fax: +45-7211-2210

## • Russia

### Anritsu EMEA Ltd.

**Representation Office in Russia**  
Tverskaya str. 16/2, bld. 1, 7th floor  
Moscow, 125009, Russia  
Phone: +7-495-363-1694  
Fax: +7-495-935-8962

## • Spain

### Anritsu EMEA Ltd.

**Representation Office in Spain**  
Edificio Cuzco IV, Po. de la Castellana, 141, Pta. 8  
28046, Madrid, Spain  
Phone: +34-915-726-761  
Fax: +34-915-726-621

## • United Arab Emirates

### Anritsu EMEA Ltd.

**Dubai Liaison Office**  
902, Aurora Tower,  
P O Box: 500311- Dubai Internet City  
Dubai, United Arab Emirates  
Phone: +971-4-3758479  
Fax: +971-4-4249036

## • India

### Anritsu India Private Limited

2nd & 3rd Floor, #837/1, Binnamangla 1st Stage  
Indiranagar, 100ft Road, Bangalore - 560038, India  
Phone: +91-80-4058-1300  
Fax: +91-80-4058-1301

## • Singapore

### Anritsu Pte. Ltd.

11 Chang Charn Road, #04-01, Shiro House  
Singapore 199640  
Phone: +65-6282-2400  
Fax: +65-6282-2533

## • P.R. China (Shanghai)

### Anritsu (China) Co., Ltd.

27th Floor, Tower A  
New Caohejing International Business Center  
No. 391 Gui Ping Road Shanghai, Xu Hui Di District  
Shanghai 200233, P.R. China  
Phone: +86-21-6237-0898  
Fax: +86-21-6237-0899

## • P.R. China (Hong Kong)

### Anritsu Company Ltd.

Unit 1006-7, 10/F., Greenfield Tower  
Concordia Plaza  
No. 1 Science Museum Road, Tsim Sha Tsui East  
Kowloon, Hong Kong, P. R. China  
Phone: +852-2301-4980  
Fax: +852-2301-3545

## • Japan

### Anritsu Corporation

8-5, Tamura-cho, Atsugi-shi  
Kanagawa, 243-0016 Japan  
Phone: +81-46-296-1221  
Fax: +81-46-296-1238

## • Korea

### Anritsu Corporation, Ltd.

5FL, 235 Pangyoek-ro, Bundang-gu, Seongnam-si  
Gyeonggi-do, 13494 Korea  
Phone: +82-31-696-7750  
Fax: +82-31-696-7751

## • Australia

### Anritsu Pty. Ltd.

Unit 20, 21-35 Ricketts Road,  
Mount Waverley, Victoria 3149, Australia  
Phone: +61-3-9558-8177  
Fax: +61-3-9558-8255

## • Taiwan

### Anritsu Company Inc.

7F, No. 316, Sec. 1, Neihu Rd, Taipei 114, Taiwan  
Phone: +886-2-8751-1816  
Fax: +886-2-8751-1817

List Revision Date: 20160317

Data subject to change without notice.

For the most recent specifications, visit: [www.anritsu.com](http://www.anritsu.com).

8 of 8

MS27102A TDS, PN: 11410-00847, Rev. J

Copyright May 2017, Anritsu Company, USA. All Rights Reserved.

® Anritsu All trademarks are registered trademarks of their respective companies.

Anritsu utilizes recycled paper and environmentally conscious inks and toner.